

Monitor Software1)	MMS (M3001A/M3001AL)2)											
	HW A #A01 (SN Prefix (SNP) DE227, DE441)											
	HW B (#A01 SNP DE512) (#A02 SNP DE441, DE512)											
	HW C (#A01, #A02, #A03, #A043) SNP DE610, DE632, DE717, DE907, DE345, DE420, DE468, DE522, DE563)											
B.0	B.1	C.0	D.0	E.0	F.0	G.0	H.15	J.0	K.2	L.0	M.0x	
A.2	O	O	O	O	O	O	O	X	X	X	X	X
B.0	O	O	O	O	O	O	O	O	O5)	O5)	O5)	O5)
B.1	O	O	O	O	O	O	O	O	O	O	O	O
C.0	O	O	O	O	O	O	O	O	O	O	O	O
D.0	O	O	O	O	O	O	O	O	O	O	O	O
E.0	X	X	O	O	O	O	O	O	O	O	O	O
F.0	X	X	O	O	O	O	O	O	O	O	O	O
G.0	X	X	X	O	O	O	O	O	O	O	O	O
H.15	X	X	X	X	X	O	O	O	O	O	O	O
J.x	X	X	X	X	X	O	O	O	O	O	O	O
K.2	X	X	X	X	X	X	O4)	O	O	O	O	O
L.x	X	X	X	X	X	X	O4)	O	O	O	O6)	O
M.0x	X	X	X	X	X	X	O4)	O	O	O	O	O

1) It is recommended to run the MMS on the same software version than the host monitor, otherwise release-specific functionality might not be available.

2) M3001AL is based on HW C; requires software L.0 or higher

3) M3001A #A04 must not be downgraded below F.0

4) Not with MX400/430/450/500/550

5) NBP repeat times of 1 h and above are shown as question marks only

6) XG50 L.12 requires MMS on L.0 (or higher)